SIEMENS

SIREMOBIL

SP

Update Instructions SP019/03/P

Title: DICOM Connect, Change of the UPS

Reason for Update:		☒ Performance
Urgency:	☐ Immediate	☒ Within 3 months
Update material required?	☒ Yes	☐ No
Materials free of charge?	☒ Yes	☐ No
Return of parts?	☒ Yes	☐ No
Estimated completion time:	1 hour	Number of CSE's: 1
Customer application training?	☐ Yes	☒ No

Systems/Products affected/System identifying IVK

Name	Material No.	Serial No.
SIREMOBIL Compact,	37 76 494	n.a.
SIREMOBIL Compact L	37 80 629	n.a.
SIREMOBIL Iso-C	28 29 450	n.a.
POWERMOBIL	28 30 011	n.a.
ARCOSKOP	47 74 019	n.a.

Remark: n.a.

Components affected/to be modified

Name	Material No.	Serial No.	Component status affected
DICOM Connect	71 41 257	see list (page 2)	n.a.

Remark: n.a.

Chg. Ref. No.: 120 333
Name: Arnold
Dept.: CS PS 24

© Siemens AG 2003
The reproduction, transmission or use of this document or its contents is not permitted without express written authority. Offenders will be liable for damages. All rights, including rights created by patent grant or registration of a utility model or design, are reserved.

Document Revision Level

This document corresponds to the version/revision level effective at the time of system delivery. Revisions to hardcopy documentation are not automatically distributed.

Please contact your local Siemens office to order current revision levels.

Disclaimer

The installation and service of equipment described herein is to be performed by qualified personnel who are employed by Siemens or one of its affiliates or who are otherwise authorized by Siemens or one of its affiliates to provide such service.

Assemblers and other persons who are not employed by or otherwise directly affiliated with or authorized by Siemens or one of its affiliates are directed to contact one of the local offices of Siemens or one of its affiliates before attempting installation or service procedures.

Systems/Products Affected

All SIREMOBIL Compact, SIREMOBIL Compact L, SIREMOBIL Iso-C, POWERMOBIL and ARCOSKOP systems, delivered or upgraded with the Option DICOM Connect, Part No. 71 41 257.

Part	**Serial No.**
DICOM Connect, Part No. 71 41 257	02-1306
	02-1385
	03-0029
	03-0030
	03-0031
	03-0064
	03-0065
	03-0126
	03-0127
	03-0128
	03-0215
	03-0216
	03-0217
	03-0218

Reason for the Update

Improvement of the reliability

Prerequisites

n.a.

Special Tools / Documents

- Installation instructions APC USV Upgrade (included in Update kit 71 41 224)
- 1 Set Allen keys
- Service tool case

Ordering Information

The following update kit has to be ordered from CSML (SAP Distribution Channel, factory 2050):

Update Kit **Update USV, Part No. 71 41 224**

List the system Serial Number on the order!

Contents of the Update Kit

See Installation instructions APC USV Upgrade

Return of Parts

The following parts must be returned:

Uninterruptable power supply (manufacturer Lieberth) 71 41 240

All parts must be correctly packaged!
No credit will be issued for returned parts that have been damaged as a result of incorrect handling.
These parts must be returned in accordance with ARTD Returned Parts using the Returned Parts form.

Work Steps

- Switch off the system and disconnect the power plug from the power wall socket.
- Open the rear cover of the monitor cart.
- Pull out the option DICOM Connect. If needed, temporarily disconnect the two short cables, and reconnect it.
- Perform the update as described in the Installation Instructions APC USV Upgrade.
- Reinstall the option DICOM Connect in the upper tray of the monitor cart.
- Reinstall all connectors, protective ground wires and cables.

Final work steps

Covers

- Close all covers.

System and safety tests

- Perform the protective conductor test in accordance with ARTD - 002.731.17.
  The protective conductor resistance must not exceed 0.2 Ohms.
- Switch on the system.
- Check the boot up of the DICOM Connect

  ➪ The option DICOM Connect must boot up correctly, and after boot-up the main menu must be visible at the DICOM Connect TFT monitor.
- Switch off the system.

  ➪ After approx. 1 minute, the DICOM Connect PC must shut down automatically. After approx. 2 - 3 minutes, the DICOM Connect PC must be off.
- Perform a final check. Check the overall function of the system.
- File the update instructions in the system binder or the system log book.
- Fill out, and if needed, copy the attached "Update Completion Form" and insert it into Register 10 of the System Binder or System Logbook.

Customer Information

Hand over the user manual, delivered with the update kit, to the customer.

Final Work Steps

n.a.

Changes to Previous Version

n.a.

Completion Protocol

The update with the number **SP019/03/P** has been completed.

Material number: .....

Serial number: .....

Customer: ..... Functional Location: .....

Customer No.: .....

Name (CSE): ..... Telephone: .....

Country: ..... Location: .....

Date: ..... Signature: .....

Remark: .....

.....

NOTE

After completing the update, make a copy of this page, fill it out and file it in the corresponding System Binder/User Handbook.

This page intentionally left blank.